

Yamaha PM5D-RH PC Card Setup Directions for KLTy Celebrate Freedom (FOH and Monitors)

1. Create your scene with the input list and output list provided.
2. Store your scene **with all outputs muted** to location **099**. **Make sure your Input Patch, Output Patch and Head Amp libraries are also stored to location 099.**
3. Insert your PC Card.
4. Go to the **Utility | Save** page and select the **BASIC** mode option at the top left.
5. Select the **Scene Memory** and **Linked Library** buttons. (BASIC, Scene Memory and Linked Library buttons should be the only buttons showing green)
6. Next to the **Scene Memory** button select the number field and select **099**
7. Next to the **Linked Library** button select the number field and select **099**
8. Select **SAVE** in the middle of the screen.
9. When the File Save dialog box comes up, name the file either: **KLTYSL-H (for FOH), or KLTYSL-M (for monitors)**. **No other file names will be accepted.**
10. **Prior to Wednesday before the event, send a copy of your inputs and your monitor mix outputs on our master list file to: espoto@crossroadsaudio.com.**

Notes:

1. Do not deviate from the Master Input list. (i.e. keep vocals in the Master vocal inputs section, electric and acoustic guitars in the Master electric and acoustic guitar inputs sections, drums in the drum inputs section, keys in the Master key inputs section, etc)
2. Do not deviate from the Master Monitor Mixes/Output Assignments list. (i.e. note the wedge and sidefill locations/mix outputs, the IEM mix outputs and the effects mix outputs and do not change the assignments)
3. Any file not in the format specified above will be rejected.

If you have any questions, please call Ed Spoto @ 214-358-2623